

# XMT-32S

## *Transmitter Controller*




### **DESCRIPTION**

The XMT-32S Transmitter Controller produces timing signals for controlling all of the Zonge Engineering GGT, ZT and NT transmitters. Provision is made for synchronizing multiple controllers and GDP receivers. Frequency control can be accomplished either manually or by a time sequence program which is loaded through the RS-232c port. Time sequence status and frequency are displayed on an LCD on the front panel.

### **FEATURES**

- Time or frequency domain control
- Frequency range: 1024 second period to 8192 Hz
- Compatible with all Zonge-series transmitters
- Automatic transmitter control via time table
- Calibrator output
- LCD frequency display



**Zonge Engineering and Research Organization, Inc.**

*Specialists in Electrical Geophysics*

• *Field Surveys* • *Geophysical Consulting* • *Instrumentation Sales and Lease* •

# SPECIFICATIONS FOR THE XMT-32S TRANSMITTER CONTROLLER

## General

Synchronous time-base with internal calibrator  
Time or Frequency domain capability, 50% or 100% Duty cycle  
Frequency range in Binary Steps:  
1024 sec. to 8192 Hz  
Size: 28 x 21 x 18 cm (11 x 8 x 7 in)  
Weight: 6.4 kg (14 lb)  
Enclosure: Heavy duty, environmentally sealed aluminum case  
Power: 12 V rechargeable battery  
more than 10 hours continuous operation  
Temperature range: - 40° to +60°C (- 40° to 140°F)  
Humidity range: 0 to 95% non-condensing  
Time base: Oven-controlled crystal oscillator;  
aging rate  $<5 \times 10^{-10}$  per 24 hours  
(optional crystal:  $1 \times 10^{-11}$  per 24 hours)

## Displays & Controls

LCD frequency display  
Phase/Battery meter  
Time/Frequency domain switch  
Phase/Battery meter switch  
Calibrate output switch:  
0.025 / 0.25 / 2.5V PP  
Reset switch  
Frequency range stepping switch  
Auto/Manual switch for time table operation  
Mode stepping switch  
Circuit Breaker

## Outputs & Inputs

12V Battery charge input  
Transmitter control/synchronization Input/Output  
RS-232c Input/Output for time series  
Calibrate output

## Functions

Can be synchronized with Zonge-series receivers for synchronous measurements  
Designed to control Zonge-series transmitters in both time and frequency domain  
Continuous phase coherency between 1024 second period and 8192 Hz  
20 milliamp signal outputs for transmitter control  
Reset pulse output for GDP-series receiver  
Capable of controlling other manufacturer's transmitters (Inquire for Compatibility)

*Specifications subject to change without notice  
© Copyright 1998, Zonge Engineering & Research Organization, Inc.*



## Zonge Engineering and Research Organization, Inc.

### Offices:

Arizona, Alaska, Nevada, Colorado and Minnesota

### Headquarters:

3322 E. Ft. Lowell Road, Tucson, AZ 85716, USA (800) 523-9913  
Tel: (520) 327-5501 Email: zonge@zonge.com  
Fax: (520) 325-1588 Web: <http://www.zonge.com>